

# Product data sheet

Specifications



## universal protection relay, PowerLogic P3U 3CT 11o 14DI 11DO 48-230V DI110 2RJ45 RL

REL53131

Product availability: Non-Stock - Not normally stocked in distribution facility

**Price\*: 2,341.63 USD**

### Main

Range of Product	PowerLogic P3
Product or Component Type	Protection relay
Relay application	Universal
product reference	P3U30-6AAA2BHAB
Mounting case size	30TE
Device mounting	Flush
Mounting Mode	Flush mounting
power supply	48...230 V AC/DC
measuring inputs	3 1/5 A CT phase current 1 1/5 A CT residual current 4 100 V/110 V VT voltage
number of Digital Inputs (DI)	16
number of analogue inputs	0
number of Digital Outputs (DO)	8 DO 1 watchdog
number of analogue outputs	0
communication ports	Front USB port 1 Rear RJ45 2
communication protocols	IEC 61850 ed. 1 IEC 61850 ed. 2 IEC 60870-5-101 DNP3 TCP Modbus TCP EtherNet/IP
Redundancy communication port protocol	RSTP PRP
Cybersecurity	Password protection Port hardening

Price is "List Price" and may be subject to a trade discount – check with your local distributor or retailer for actual price.

<b>protection functions</b>	<ul style="list-style-type: none"> <li>Phase overcurrent 50/51</li> <li>Directional phase overcurrent 67</li> <li>Earth fault overcurrent 50N/51N</li> <li>Directional earth fault 67N</li> <li>Transient earth fault 67NI</li> <li>Capacitor bank unbalance 51C</li> <li>Broken conductor 46 I2/I1</li> <li>Cold load pick-up</li> <li>H2 detection 68H2</li> <li>H5 detection 68H5</li> <li>Cold load pick-up 21FL</li> <li>Breaker failure 50BF</li> <li>Switch ON to fault (SOTF)</li> <li>Directional active underpower 37P</li> <li>Fault locator 21FL</li> <li>Recloser 79</li> <li>Phase undercurrent 37</li> <li>Excessive starting time, locked rotor 48/51LR</li> <li>Motor restart inhibition 66</li> <li>Capacitor overvoltage 59C</li> <li>Switch ON to fault (SOTF) 60</li> <li>Negative sequence overcurrent 46</li> <li>Overvoltage 59</li> <li>Undervoltage 27</li> <li>Positive sequence undervoltage 27P</li> <li>Earth fault overvoltage 59N</li> <li>Underfrequency 81/81N</li> <li>Rate of change of frequency 81R</li> <li>Synchro-check 25</li> <li>Lockout relay 86</li> <li>CT supervision 60</li> <li>VT supervision 60</li> <li>Programmable stages 99 8</li> <li>Programmable curve</li> </ul>
-----------------------------	--

<b>Arc flash protection</b>	No
-----------------------------	----

<b>measurement functions</b>	<ul style="list-style-type: none"> <li>Current 3-phase</li> <li>Current zero sequence</li> <li>Current positive sequence</li> <li>Current negative sequence</li> <li>Current ratio of negative and positive</li> <li>Voltage phase to earth</li> <li>Voltage phase to phase</li> <li>Voltage zero sequence</li> <li>Voltage positive sequence</li> <li>Voltage negative sequence</li> <li>Voltage ratio of negative and positive</li> <li>Short circuit fault reactance</li> <li>Fault location current</li> <li>Short circuit fault reactance zero sequence</li> <li>Earth fault reactance</li> <li>Frequency</li> <li>Active power</li> <li>RMS active power</li> <li>Reactive power</li> <li>Fault location current positive sequence</li> <li>RMS reactive power</li> <li>Apparent power</li> <li>RMS apparent power</li> <li>Active energy</li> <li>Reactive energy</li> <li>Earth fault reactance negative sequence</li> <li>Cos <math>\varphi</math></li> <li>Tan <math>\varphi</math></li> <li>Power angle</li> <li>Power factor</li> <li>Voltage phasor diagram view</li> <li>Frequency ratio of negative and positive</li> <li>Current phasor diagram view</li> <li>Current 2nd, 15th harmonics with THD</li> <li>Voltage 2nd, 15th harmonics with THD</li> <li>Condition monitoring CB wear</li> <li>Voltage interruption</li> <li>Active power phase to earth</li> <li>RMS active power phase to phase</li> <li>Reactive power positive sequence</li> <li>RMS reactive power ratio of negative and positive</li> <li>Condition monitoring CB wear 2nd, 15th harmonics with THD</li> </ul>
------------------------------	---

<b>control functions</b>	Switchgear control and monitoring Programmable switchgear interlocking Local control on single-line diagram Local control with I/O keys Local/remote control 2 function keys Mobile application with Easergy SmartApp Web-server Programmable logic
<b>controllable switchgear devices</b>	4 controlled + 8 displayed
<b>number of setting groups</b>	4
<b>monitoring functions</b>	Trip circuit supervision 74 Circuit breaker monitoring Relay self-monitoring
<b>logs and records</b>	Event recording Disturbance recording Tripping context
<b>Switchgear diagnosis type</b>	CT supervision TCS Trip circuit supervision TCS
<b>Connections - terminals</b>	Screw removable (digital input/output) Pin removable (voltage transformer) Pin removable (current transformer)

## Complementary

<b>Operating threshold</b>	110...230 V AC/DC
<b>Time synchronisation protocol</b>	SNTP
<b>Software name</b>	ESetup Easergy Pro virtual simulation test Easergy SmartApp
<b>Web server</b>	Embedded HTTP server
<b>Display type</b>	LCD 128 x 64 pixels with single line diagram
<b>Number of key</b>	2 customizable
<b>Local signalling</b>	4 LEDs 8 LEDs programmable
<b>Height</b>	6.7 in (169.5 mm)
<b>Width</b>	6.7 in (170 mm)
<b>Depth</b>	8.07 in (205 mm)
<b>Net weight</b>	5.5 lb(US) (2.5 kg) maximum

## Environment

<b>climatic withstand</b>	Exposure to dry heat Bb EN/IEC 60068-2-2 Exposure to cold Ad EN/IEC 60068-2-1 Exposure to damp heat in service Db EN/IEC 60068-2-30 Exposure to damp heat in service Cab EN/IEC 60068-2-78
<b>Mechanical robustness</b>	Vibrations class II) IEC 60255-21-1 VibrationsFc IEC 60068-2-6 Shocks class II) IEC 60255-21-2 ShocksEa IEC 60068-2-27 Seismic tests method A class II) IEC 60255-21-3

<b>Electromagnetic compatibility</b>	Emission tests IEC/EN 60255-26 ed. 3 Emission tests class A CISPR 11 Emission tests class A CISPR 22 EMC immunity IEC/EN 60255-26 ed. 3 EMC immunity EN/IEC 61000-4-18 EMC immunity level 4 EN/IEC 61000-4-2 EMC immunity level 3 EN/IEC 61000-4-3 EMC immunity level 4 EN/IEC 61000-4-4 EMC immunity level 3 EN/IEC 61000-4-5 EMC immunity level 3 EN/IEC 61000-4-6 EMC immunity EN/IEC 61000-4-8 EMC immunity level 5 EN/IEC 61000-4-9 EMC immunity EN/IEC 61000-4-29 EMC immunity EN/IEC 61000-4-11 EMC immunity EN/IEC 61000-4-17
<b>Ambient air temperature for operation</b>	-40...149 °F (-40...65 °C)
<b>IP degree of protection</b>	IP54 front IEC 60529
<b>maximum operating altitude</b>	6561.68 ft (2000 m)
<b>Protective treatment</b>	Conformal coating
<b>Relative humidity</b>	0...95 %, without condensation

## Ordering and shipping details

<b>Category</b>	US1PL1S11405
<b>Discount Schedule</b>	PL1S
<b>GTIN</b>	3606487106982
<b>Returnability</b>	No
<b>Country of origin</b>	US

## Packing Units

<b>Unit Type of Package 1</b>	PCE
<b>Number of Units in Package 1</b>	1
<b>Package 1 Height</b>	15.75 in (40 cm)
<b>Package 1 Width</b>	11.81 in (30 cm)
<b>Package 1 Length</b>	11.81 in (30 cm)
<b>Package 1 Weight</b>	8.4 lb(US) (3.8 kg)

## Contractual warranty

<b>Warranty</b>	Up to 10 years (Standard warranty 2 years. Please check with your local SE representative for extended warranty availability and conditions)
-----------------	--

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard **Yes**

Packaging without single use plastic **No**

EU RoHS Directive **Compliant with Exemptions**

REACH Regulation [REACH Declaration](#)

China RoHS Regulation [China RoHS declaration](#)

## Use Again

### Repack and remanufacture

[Circularity Profile](#)

[End of Life Information](#)

WEEE



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins.

Take-back

No

---