

Product datasheet

Specifications



capacitor - C60 - Sepam series 60

59795

Main

Relay application	Capacitor
Range of product	Sepam series 60
Device short name	C60
Control and monitoring type	Circuit breaker/contactor control ANSI code: 94/69 (option) Latching/acknowledgement ANSI code: 86 Logic discrimination ANSI code: 68 (option) Switching of groups of settings Annunciation ANSI code: 30 Automatic transfer (AT) (option) Logic equation editor 200 operators
Metering type	Positive sequence voltage Vd/rotation direction Frequency Calculated active and reactive energy (+/- W.h, +/- VAR.h) Active and reactive energy by pulse counting (+/- W.h, +/- VAR.h) (option) Phase current I1, I2, I3 RMS Demand current I1, I2, I3 Peak demand current IM1, IM2, IM3 Voltage U21, U32, U13, V1, V2, V3 Residual voltage V0 Negative sequence voltage Vi Active power P, P1, P2, P3 Reactive power Q, Q1, Q2, Q3 Apparent power S, S1, S2, S3 Peak demand power PM, QM Power factor Measured residual current I0, calculated I'0Σ
Network and machine diagnosis type	Unbalance ratio/negative sequence current li Disturbance recording Thermal capacity used Remaining operating time before overload tripping Waiting time after overload tripping Running hours counter/operating time Tripping context Phase fault and earth fault trip counters Harmonic distortion (THD), current and voltage Ithd, Uthd Apparent positive sequence impedance Zd Apparent phase-to-phase impedances Z21, Z32, Z13 Cable arcing fault detection Phase displacement Datalog (DLG)
Switchgear diagnosis type	Cumulative breaking current CT/VT supervision ANSI code: 60FL Trip circuit supervision ANSI code: 74 (option) Nb of operations, operating time, charging time, nb of racking out operations (option)

Complementary

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

Type of measurement	Power (P,Q) Frequency Harmonic distortion (I THD & U THD) Current Power factor Voltage Peak demand power Energy
Protection type	Neutral voltage displacement ANSI code: 59N (2) Breaker failure ANSI code: 50BF (1) Temperature monitoring (16 RTDs) ANSI code: 38/49T (option) Phase overcurrent ANSI code: 50/51 (4) Earth fault/sensitive earth fault ANSI code: 50N/51N (4) Earth fault/sensitive earth fault ANSI code: 50G/51G (4) Negative sequence/unbalance ANSI code: 46 (2) Overfrequency ANSI code: 81H (2) Underfrequency ANSI code: 81L (4) Positive sequence undercurrent ANSI code: 27D (2) Remanent undervoltage ANSI code: 27R (2) Negative sequence overvoltage ANSI code: 47 (2) Undervoltage (L-L or L-N) ANSI code: 27 (2) Overvoltage (L-L or L-N) ANSI code: 59 (2) Thermal overload for capacitors ANSI code: 49RMS (1)
Communication port protocol	Measurement readout (option) : Modbus Remote indication and time tagging of events (option) : Modbus Remote control orders (option) : Modbus Remote protection setting (option) : Modbus Transfer of disturbance recording data (option) : Modbus
Input output max capacity	28 inputs + 16 outputs
Communication compatibility	DNP3 Modbus TCP/IP Modbus RTU IEC 61850 IEC 60870-5-103 IEC 61850 goose message
User machine interface type	Remote Advanced Mimic-based Without

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	1.0 cm
Package 1 Width	1.0 cm
Package 1 Length	1.01 cm
Package 1 Weight	100.0 g