

Product datasheet

Specifications



REL52078 discontinued. To order it, click on blue Product Selector button, configure P3U30, and use its output xml file

REL52078

Main

Range of product	Easergy P3
Product or component type	Protection relay
Relay application	Universal
product reference	P3U30-7AAA1CBAA
Device mounting	Flush
power supply	48...230 V AC/DC
measuring inputs	: LPCT phase current 3 : 1/5 A CT residual current 1 : LPVT voltage 5
number of Digital Inputs (DI)	16
number of Digital Outputs (DO)	8 DO 1 watchdog
number of analogue outputs	0
communication ports	USB port 1 front RS485 1 rear
communication protocols	IEC 60870-5-101 IEC 60870-5-103 DNP3 Modbus RTU DeviceNet SPAbus
Cybersecurity	Password protection Port hardening

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

protection functions	Phase overcurrent 50/51
	Directional phase overcurrent 67
	Earth fault overcurrent 50N/51N
	Directional earth fault 67N
	Transient earth fault 67NI
	Capacitor bank unbalance 51C
	Broken conductor 46 I2/I1
	Cold load pick-up
	H2 detection 68H2
	H5 detection 68H5
	Breaker failure 50BF
	Switch ON to fault (SOTF)
	Directional active underpower 37P
	Fault locator 21FL
	Recloser 79
	Phase undercurrent 37
	Excessive starting time, locked rotor 48/51LR
	Motor restart inhibition 66
	Capacitor overvoltage 59C
	Negative sequence overcurrent 46
	Overvoltage 59
	Undervoltage 27
	Positive sequence undervoltage 27P
	Earth fault overvoltage 59N
	Underfrequency 81/81N
	Rate of change of frequency 81R
	Synchro-check 25
	Lockout relay 86
	CT supervision 60
	VT supervision 60
	Programmable stages 99
	Programmable curve
Arc flash protection	No
measurement functions	Current 3-phase
	Current zero sequence
	Current positive sequence
	Current negative sequence
	Current ratio of negative and positive
	Voltage phase to earth
	Voltage phase to phase
	Voltage zero sequence
	Voltage positive sequence
	Voltage negative sequence
	Voltage ratio of negative and positive
	Short circuit fault reactance
	Fault location current
	Earth fault reactance
	Frequency
	Active power
	RMS active power
	Reactive power
	RMS reactive power
	Apparent power
	RMS apparent power
	Active energy
	Reactive energy
	Cos ϕ
	Tan ϕ
	Power angle
	Power factor
	Voltage phasor diagram view
	Current phasor diagram view
	Current 2nd, 15th harmonics with THD
	Voltage 2nd, 15th harmonics with THD
	Condition monitoring CB wear
	Voltage interruption
control functions	Switchgear control and monitoring
	Programmable switchgear interlocking
	Local control on single-line diagram
	Local control with I/O keys
	Local/remote control
	2 function keys
	Mobile application with Easergy SmartApp
controllable switchgear devices	Web-server
	4 controlled + 8 displayed

number of setting groups	4
monitoring functions	Trip circuit supervision 74 Circuit breaker monitoring Relay self-monitoring
logs and records	Event recording Disturbance recording Tripping context
Switchgear diagnosis type	CT supervision Trip circuit supervision ANSI code: TCS
Connections - terminals	Screw removable (digital input/output) Pin removable (current transformer) Pin removable (voltage transformer)

Complementary

Operating threshold	24 V AC/DC
Display type	LCD 128 x 64 pixels with single line diagram
Number of key	2 customizable
Local signalling	4 LEDs 8 LEDs programmable
Height	169.5 mm
Width	170 mm
Depth	205 mm
Net weight	2.5 kg maximum

Environment

climatic withstand	Exposure to dry heat Bd tests conforming to EN/IEC 60068-2-2 Exposure to cold Ad tests conforming to EN/IEC 60068-2-1 Exposure to damp heat in service Db tests conforming to EN/IEC 60068-2-30 Exposure to damp heat in service Cab tests conforming to EN/IEC 60068-2-78
Mechanical robustness	Vibrations (level: class II) conforming to IEC 60255-21-1 Vibrations: Fc conforming to IEC 60068-2-6 Shocks (level: class II) conforming to IEC 60255-21-2 Shocks: Ea conforming to IEC 60068-2-27 Seismic tests method A (level: class II) conforming to IEC 60255-21-3
Electromagnetic compatibility	Emission tests conforming to IEC/EN 60255-26 ed. 3 Emission tests class A conforming to CISPR 11 Emission tests class A conforming to CISPR 22 EMC immunity conforming to IEC/EN 60255-26 ed. 3 EMC immunity conforming to EN/IEC 61000-4-18 EMC immunity conforming to IEC 60255-22-1 EMC immunity level 4 conforming to EN/IEC 61000-4-2 EMC immunity conforming to IEC 60255-22-2 EMC immunity level 3 conforming to EN/IEC 61000-4-3 EMC immunity conforming to IEC 60255-22-3 EMC immunity level 4 conforming to EN/IEC 61000-4-4 EMC immunity conforming to IEC 60255-22-4 EMC immunity level 3 conforming to EN/IEC 61000-4-5 EMC immunity conforming to IEC 60255-22-5 EMC immunity level 3 conforming to EN/IEC 61000-4-6 EMC immunity conforming to IEC 60255-22-6 EMC immunity conforming to EN/IEC 61000-4-8 EMC immunity level 5 conforming to EN/IEC 61000-4-9 EMC immunity conforming to EN/IEC 61000-4-29 EMC immunity conforming to EN/IEC 61000-4-11 EMC immunity conforming to EN/IEC 61000-4-17 EMC immunity conforming to IEC 60255-27 EMC immunity class III conforming to IEC 60255-5 EMC immunity conforming to EN/IEC 60255-1
Ambient air temperature for operation	-40...65 °C
maximum operating altitude	2000 m

Protective treatment	Conformal coating
Relative humidity	0...95 %, without condensation

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1
Package 1 Height	29.0 cm
Package 1 Width	30.0 cm
Package 1 Length	40.0 cm
Package 1 Weight	3.51 kg



Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)



Environmental footprint

Environmental Disclosure

[Product Environmental Profile](#)

Use Better



Materials and Substances

Packaging made with recycled cardboard	No
--	----


Packaging without single use plastic	No
--------------------------------------	----

EU RoHS Directive	Compliant with Exemptions
-------------------	---------------------------

REACH Regulation	REACH Declaration
------------------	-----------------------------------

China RoHS Regulation	China RoHS declaration
-----------------------	--

Use Again



Repack and remanufacture

Circularity Profile

[End of Life Information](#)

WEEE



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Take-back

No
