

# Product data sheet

Specifications



universal protection relay,  
PowerLogic P3U 3CT 1Io RINGLUG  
4VT 8DI 16DO 48-230V DI110V  
RS485 ANSI

REL53002

## Main

Range of product	PowerLogic P3
Product or component type	Protection relay
Relay application	Universal
product reference	P3U30-6AAA2BEAB
Mounting case size	30TE
Device mounting	Flush
Mounting mode	Flush mounting
power supply	48...230 V AC/DC
measuring inputs	3 1/5 A CT phase current 1 1/5 A CT residual current 4 100 V/110 V VT voltage
number of Digital Inputs (DI)	16
number of analogue inputs	0
number of Digital Outputs (DO)	8 DO 1 watchdog
number of analogue outputs	0
communication ports	Front USB port 1 Rear RS232 1 Rear RJ45 1
communication protocols	IEC 60870-5-101 IEC 60870-5-103 DNP3 Modbus RTU DeviceNet SPAbus
Cybersecurity	Password protection Port hardening

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

<b>protection functions</b>	<ul style="list-style-type: none"> <li>Phase overcurrent 50/51</li> <li>Directional phase overcurrent 67</li> <li>Earth fault overcurrent 50N/51N</li> <li>Directional earth fault 67N</li> <li>Transient earth fault 67NI</li> <li>Capacitor bank unbalance 51C</li> <li>Transient earth fault 67NI 8</li> <li>Broken conductor 46 I2/I1</li> <li>Cold load pick-up</li> <li>H2 detection 68H2</li> <li>H5 detection 68H5</li> <li>Breaker failure 50BF</li> <li>Switch ON to fault (SOTF)</li> <li>Directional active underpower 37P</li> <li>Cold load pick-up 60</li> <li>Fault locator 21FL</li> <li>Recloser 79</li> <li>Phase undercurrent 37</li> <li>Excessive starting time, locked rotor 48/51LR</li> <li>Motor restart inhibition 66</li> <li>Capacitor overvoltage 59C</li> <li>Negative sequence overcurrent 46</li> <li>Overvoltage 59</li> <li>Undervoltage 27</li> <li>Positive sequence undervoltage 27P</li> <li>Earth fault overvoltage 59N</li> <li>Underfrequency 81/81N</li> <li>Rate of change of frequency 81R</li> <li>Synchro-check 25</li> <li>Lockout relay 86</li> <li>CT supervision 60</li> <li>VT supervision 60</li> <li>Programmable stages 99 8</li> <li>Programmable curve</li> <li>Programmable curve 86</li> </ul>
-----------------------------	---

<b>Arc flash protection</b>	No
-----------------------------	----

<b>measurement functions</b>	<ul style="list-style-type: none"> <li>Current 3-phase</li> <li>Current zero sequence</li> <li>Current positive sequence</li> <li>Current negative sequence</li> <li>Current ratio of negative and positive</li> <li>Voltage phase to earth</li> <li>Voltage phase to phase</li> <li>Voltage zero sequence</li> <li>Voltage positive sequence</li> <li>Voltage negative sequence</li> <li>Voltage ratio of negative and positive</li> <li>Short circuit fault reactance</li> <li>Fault location current</li> <li>Earth fault reactance</li> <li>Fault location current phase to earth</li> <li>Frequency</li> <li>Active power</li> <li>RMS active power</li> <li>Reactive power</li> <li>RMS reactive power</li> <li>Apparent power</li> <li>Earth fault reactance phase to phase</li> <li>RMS apparent power</li> <li>Active energy</li> <li>Reactive energy</li> <li>Cos <math>\varphi</math></li> <li>Tan <math>\varphi</math></li> <li>Frequency zero sequence</li> <li>Power angle</li> <li>Power factor</li> <li>Voltage phasor diagram view</li> <li>Active power positive sequence</li> <li>Current phasor diagram view</li> <li>Current 2nd, 15th harmonics with THD</li> <li>Voltage 2nd, 15th harmonics with THD</li> <li>Condition monitoring CB wear</li> <li>Voltage interruption</li> <li>RMS apparent power positive sequence</li> <li>Active energy ratio of negative and positive</li> </ul>
------------------------------	---

<b>control functions</b>	Switchgear control and monitoring Programmable switchgear interlocking Local control on single-line diagram Local control with I/O keys Local/remote control 2 function keys Mobile application with Easergy SmartApp Web-server Programmable logic
<b>controllable switchgear devices</b>	4 controlled + 8 displayed
<b>number of setting groups</b>	4
<b>monitoring functions</b>	Trip circuit supervision 74 Circuit breaker monitoring Relay self-monitoring
<b>logs and records</b>	Event recording Disturbance recording Tripping context
<b>Switchgear diagnosis type</b>	CT supervision TCS Trip circuit supervision TCS
<b>Connections - terminals</b>	Screw removable (digital input/output) Pin removable (voltage transformer) Ring lugs removable (current transformer)

## Complementary

<b>Operating threshold</b>	110...230 V AC/DC
<b>Time synchronisation protocol</b>	SNTP
<b>Software name</b>	ESetup Easergy Pro virtual simulation test Easergy SmartApp
<b>Web server</b>	Embedded HTTP server
<b>Display type</b>	LCD 128 x 64 pixels with single line diagram
<b>Number of key</b>	2 customizable
<b>Local signalling</b>	4 LEDs 8 LEDs programmable
<b>Height</b>	6.7 in (169.5 mm)
<b>Width</b>	6.7 in (170 mm)
<b>Depth</b>	8.07 in (205 mm)
<b>Net weight</b>	5.5 lb(US) (2.5 kg) maximum

## Environment

<b>climatic withstand</b>	Exposure to dry heat Bb EN/IEC 60068-2-2 Exposure to cold Ad EN/IEC 60068-2-1 Exposure to damp heat in service Db EN/IEC 60068-2-30 Exposure to damp heat in service Cab EN/IEC 60068-2-78
<b>Mechanical robustness</b>	Vibrations class II) IEC 60255-21-1 VibrationsFc IEC 60068-2-6 Shocks class II) IEC 60255-21-2 ShocksEa IEC 60068-2-27 Seismic tests method A class II) IEC 60255-21-3

<b>Electromagnetic compatibility</b>	Emission tests IEC/EN 60255-26 ed. 3 Emission tests class A CISPR 11 Emission tests class A CISPR 22 EMC immunity IEC/EN 60255-26 ed. 3 EMC immunity EN/IEC 61000-4-18 EMC immunity level 4 EN/IEC 61000-4-2 EMC immunity level 3 EN/IEC 61000-4-3 EMC immunity level 4 EN/IEC 61000-4-4 EMC immunity level 3 EN/IEC 61000-4-5 EMC immunity level 3 EN/IEC 61000-4-6 EMC immunity EN/IEC 61000-4-8 EMC immunity level 5 EN/IEC 61000-4-9 EMC immunity EN/IEC 61000-4-29 EMC immunity EN/IEC 61000-4-11 EMC immunity EN/IEC 61000-4-17 EMC immunity IEC 60255-22-1 EMC immunity IEC 60255-22-2 EMC immunity IEC 60255-22-3 EMC immunity IEC 60255-22-4 EMC immunity IEC 60255-22-5 EMC immunity IEC 60255-22-6 EMC immunity IEC 60255-27 EMC immunity class III IEC 60255-5 EMC immunity EN/IEC 60255-1
<b>Ambient air temperature for operation</b>	-40...149 °F (-40...65 °C)
<b>IP degree of protection</b>	IP54 front IEC 60529
<b>maximum operating altitude</b>	2000 m
<b>Protective treatment</b>	Conformal coating
<b>Relative humidity</b>	0...95 %, without condensation

## Packing Units

<b>Unit Type of Package 1</b>	PCE
<b>Number of Units in Package 1</b>	1
<b>Package 1 Height</b>	15.75 in (40 cm)
<b>Package 1 Width</b>	11.81 in (30 cm)
<b>Package 1 Length</b>	11.81 in (30 cm)
<b>Package 1 Weight</b>	8.4 lb(US) (3.8 kg)

## Contractual warranty

<b>Warranty</b>	Up to 10 years (Standard warranty 2 years. Please check with your local SE representative for extended warranty availability and conditions)
-----------------	--

## Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

### Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

## Use Better

### Materials and Substances

Packaging made with recycled cardboard **No**

Packaging without single use plastic **No**

EU RoHS Directive **Compliant with Exemptions**

REACH Regulation [REACH Declaration](#)

China RoHS Regulation [China RoHS declaration](#)

## Use Again

### Repack and remanufacture

[Circularity Profile](#)

[End of Life Information](#)

WEEE



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Take-back

No

---