

Product data sheet

Specifications



feeder protection relay, PowerLogic
P3F30 3CT 2Io ringlug 4VT 6DI
9DO 110-230V DI24V RS485 RJ45
ANSI

REL53093

Main

Range of product	PowerLogic P3
Product or component type	Protection relay
Relay application	Feeder
product reference	P3F30-CGAAA-AA1FA-BAAAB
Mounting case size	30TE
Device mounting	Flush
Mounting mode	Flush mounting
power supply	48...230 V AC/DC
measuring inputs	3 1/5 A CT phase current 1 5/1 A CT residual current 1 1/0.2 A CT residual current 4 100 V/110 V VT voltage
number of Digital Inputs (DI)	6
number of analogue inputs	0
number of Digital Outputs (DO)	10 DO 1 watchdog
number of analogue outputs	0
communication ports	Front USB port 1 Rear RS485 1 Rear RJ45 1
communication protocols	IEC 61850 ed. 1 IEC 61850 ed. 2 IEC 60870-5-101 DNP3 TCP Modbus TCP EtherNet/IP IEC 60870-5-103 DNP3 Modbus RTU DeviceNet SPAbus
Cybersecurity	Password protection Port hardening

Disclaimer: This documentation is not intended as a substitute for and is not to be used for determining suitability or reliability of these products for specific user applications

protection functions	Fault locator 21FL
	Synchro-check 25
	Undervoltage 27
	Directional active underpower 32
	Broken conductor 46BC
	Thermal overload protection 49
	Earth fault overcurrent 50N/51N
	Phase overcurrent 50/51
	Breaker failure 50BF
	Switch ON to fault (SOTF)
	Capacitor bank unbalance 51C
	Switch ON to fault (SOTF) 59C
	Voltage-restrained overcurrent 51V
	Capacitor overvoltage 59C
	Overvoltage 59
	Earth fault overvoltage 59N
	Directional phase overcurrent 67
	Directional earth fault 67N
	Transient earth fault 67NI
	Magnetising inrush detection 68F2
	Directional phase overcurrent 67 8
	H5 detection 68H5
	Recloser 79
	Underfrequency 81/81N
	Rate of change of frequency 81R
	Lockout relay 86
	Programmable stages 99 8
	Programmable curve
	Cold load pick-up
	CT supervision 60
	VT supervision 60FL
	Programmable curve 79
	Cold load pick-up 81R
Arc flash protection	No

measurement functions	Current 3-phase Current zero sequence Current positive sequence Current negative sequence Current ratio of negative and positive Voltage phase to earth Voltage phase to phase Voltage zero sequence Voltage positive sequence Voltage negative sequence Voltage ratio of negative and positive Short circuit fault reactance Fault location current Short circuit fault reactance positive sequence Earth fault reactance Frequency Active power RMS active power Reactive power Fault location current negative sequence RMS reactive power Apparent power RMS apparent power Active energy Reactive energy Cos φ Earth fault reactance ratio of negative and positive Tan φ Power angle Power factor Voltage phasor diagram view Current phasor diagram view Frequency phase to earth Current 2nd, 15th harmonics with THD Voltage 2nd, 15th harmonics with THD Condition monitoring CB wear Active power phase to phase Voltage interruption RMS active power zero sequence Reactive power positive sequence RMS reactive power negative sequence Apparent power ratio of negative and positive Condition monitoring CB wear phasor diagram view Voltage interruption 2nd, 15th harmonics with THD
control functions	Switchgear control and monitoring Programmable switchgear interlocking Local control on single-line diagram Local control with I/O keys Local/remote control 2 function keys Mobile application with Easergy SmartApp Web-server Programmable logic
controllable switchgear devices	4 controlled + 3 displayed
number of setting groups	4
monitoring functions	Trip circuit supervision 74 Circuit breaker monitoring Relay self-monitoring
logs and records	Event recording Disturbance recording Tripping context
Switchgear diagnosis type	CT supervision TCS Trip circuit supervision TCS
Connections - terminals	Screw removable (digital input/output) Pin removable (voltage transformer) Ring lugs fixed (current transformer)

Complementary

Operating threshold	24 V AC/DC
---------------------	------------

Time synchronisation protocol	SNTP
Software name	ESetup Easergy Pro virtual simulation test Easergy SmartApp
Web server	Embedded HTTP server
Display type	LCD 128 x 128 pixels with single line diagram LCD 128 x 128 pixels with ANSI symbols
Number of key	2 customizable
Local signalling	2 LEDs 16 LEDs programmable
Height	6.9 in (176 mm)
Width	10.6 in (270 mm)
Depth	9.06 in (230 mm)
Net weight	9.3 lb(US) (4.2 kg) maximum

Environment

climatic withstand	Exposure to dry heat Bb EN/IEC 60068-2-2 Exposure to cold Ad EN/IEC 60068-2-1 Exposure to damp heat in service Db EN/IEC 60068-2-30 Exposure to damp heat in service Cab EN/IEC 60068-2-78
Mechanical robustness	Vibrations class II) IEC 60255-21-1 VibrationsFc IEC 60068-2-6 Shocks class II) IEC 60255-21-2 ShocksEa IEC 60068-2-27 Seismic tests method A class II) IEC 60255-21-3
Electromagnetic compatibility	Emission tests IEC/EN 60255-26 ed. 3 Emission tests class A CISPR 11 Emission tests class A CISPR 22 EMC immunity IEC/EN 60255-26 ed. 3 EMC immunity EN/IEC 61000-4-18 EMC immunity level 4 EN/IEC 61000-4-2 EMC immunity level 3 EN/IEC 61000-4-3 EMC immunity level 4 EN/IEC 61000-4-4 EMC immunity level 3 EN/IEC 61000-4-5 EMC immunity level 3 EN/IEC 61000-4-6 EMC immunity EN/IEC 61000-4-8 EMC immunity level 5 EN/IEC 61000-4-9 EMC immunity EN/IEC 61000-4-29 EMC immunity EN/IEC 61000-4-11 EMC immunity EN/IEC 61000-4-17 EMC immunity IEC 60255-22-1 EMC immunity IEC 60255-22-2 EMC immunity IEC 60255-22-3 EMC immunity IEC 60255-22-4 EMC immunity IEC 60255-22-5 EMC immunity IEC 60255-22-6 EMC immunity IEC 60255-27 EMC immunity class III IEC 60255-5 EMC immunity EN/IEC 60255-1
Ambient air temperature for operation	-40...149 °F (-40...65 °C)
IP degree of protection	IP54 front IEC 60529
maximum operating altitude	2000 m
Protective treatment	Conformal coating
Relative humidity	0...95 %, without condensation

Packing Units

Unit Type of Package 1	PCE
Number of Units in Package 1	1

Package 1 Height	15.75 in (40 cm)
Package 1 Width	11.81 in (30 cm)
Package 1 Length	11.81 in (30 cm)
Package 1 Weight	11.7 lb(US) (5.3 kg)

Contractual warranty

Warranty	Up to 10 years (Standard warranty 2 years. Please check with your local SE representative for extended warranty availability and conditions)
----------	--

Environmental Data

Schneider Electric aims to achieve Net Zero status by 2050 through supply chain partnerships, lower impact materials, and circularity via our ongoing “Use Better, Use Longer, Use Again” campaign to extend product lifetimes and recyclability.

[Environmental Data explained >](#)

[How we assess product sustainability >](#)

Environmental footprint

[Environmental Disclosure](#)

[Product Environmental Profile](#)

Use Better

Materials and Substances

Packaging made with recycled cardboard	No
--	----

Packaging without single use plastic	No
--------------------------------------	----

EU RoHS Directive	Compliant with Exemptions
-------------------	---------------------------

REACH Regulation	REACH Declaration
------------------	-----------------------------------

China RoHS Regulation	China RoHS declaration
-----------------------	--

Use Again

Repack and remanufacture

[Circularity Profile](#)

[End of Life Information](#)

WEEE



The product must be disposed on European Union markets following specific waste collection and never end up in rubbish bins

Take-back

No
